


## Camera 60 Casambi integrated

New

### 09.8102.DR.CB - Anthracite

Spotlight to be installed on 3-phase track with LED light source. 220- 240V, 50-60Hz power supply integrated. To be used with The Tracking Power profiles.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	1266
<b>Lamp category</b>	LED	<b>Mountings</b>	Track
<b>Power (W)</b>	20W	<b>Environment</b>	Indoor dry location
<b>CCT (K)</b>	3000K		
<b>CRI</b>	97		

### Optical

<b>Lighting type</b>	Direct
<b>LED type</b>	LED array
<b>Light distribution</b>	Symmetric
<b>Optical type</b>	Medium
<b>Beam angle (°)</b>	23
<b>Beam angle C90-270 (°)</b>	23



<b>Beam Angle:</b>	23°		
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>	
1	8838	0.41	
2	2210	0.81	
3	982	1.22	
4	552	1.62	
5	354	2.03	

Luminous flux luminaire  
1266 lm

### Electrical

<b>Frequency (Hz)</b>	50/60	<b>Insulation class</b>	I
<b>Dimmable</b>	Yes		
<b>Driver</b>	Integrated		
<b>Driver type</b>	Dimmable		
	Casambi		
<b>Emergency</b>	Without		

### Physical

<b>Color</b>	Anthracite	<b>Spot diameter (mm)</b>	60
<b>Orientation</b>	Adjustable	<b>Length (mm)</b>	111
<b>Weight (kg)</b>	0.57		
<b>Tilt (°)</b>	90		
<b>Rotation (°)</b>	360		

### Note

The control system with the Casambi version of light fixtures is directly and individually regulated wirelessly using the application FLOS Control® by Casambi.

## Camera 60 Casambi integrated



---

Honeycomb  
08.0176.14