



Easy Kap 80 Plus Square Wall-Washer

Update

■ 05.7436.74 - Black

Recessed luminaire with LED light source. Power supply not included. Installation frame not necessary. Elliptical lens included.




Main specifications

Number of heads	1	Net lumen (lm)	867
Lamp category	LED	Mountings	Ceiling recessed
Power (W)	13.4W	Environment	Indoor dry location
CCT (K)	3000K		
CRI	90		

Optical

LED type	LED array
Light distribution	Asymmetric
Optical type	Wall-washer
Beam angle (°)	26
Beam angle C90-270 (°)	29
Efficiency (lm/W)	64



Beam Angle:	26°		
h(m)	E(lx)	D(m)	
1	1693	0.59	
2	423	1.19	
3	188	1.78	
4	106	2.37	
5	68	2.97	

Luminous flux luminaire
867 lm (EXTREME CUT OFF)

Electrical

Voltage (V)	17,8	Emergency	Without
Current (mA)	700	Insulation class	III
Dimmable	Yes		
Driver	Remote excluded		
Driver type	Non Dimmable, Dimmable DALI 2, Dimmable 0-10V, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		

Physical

Color	Black
Orientation	Fixed
Trim	yes
Recessed depth (mm)	140
Weight (kg)	0,241

Easy Kap 80 Plus Square Wall-Washer



Non dimmable continuous current power supply. 15-30W, 220/240V -50/60Hz with power current selected through adjustable switch. 350mA – 15W / 400mA – 17W / 450mA – 19W / 500mA – 22W / 550mA – 24W / 600mA – 26W / 650mA – 28W / 700mA – 30W no regulable
60.9592



Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.
60.8847



Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming
60.9188



Continuous current power supply, Mains dimming, leading & trailing edge 220/240V – 50/60Hz, 300mA-14W / 350mA-17W / 400mA-19W / 450/500/600/650/700/750/800/900mA – 20W
60.9467



Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2
60.9222



Continuous current power supply, dimmable Casambi, 220/240V – 50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W / 750/800/900/1000/1050mA – 38W
60.9207