


## Easy Kap 80 Square Adjustable

03.4212.B1 - White

Recessed 12V lamp luminaire. Remote transformer not included. Installation frame not necessary.

Recessed 12V lamp luminaire. Remote transformer not included. Installation frame not necessary.



### Main specifications

<b>Number of heads</b>	1
<b>Lamp category</b>	Halogen, LED retrofit
<b>Power (W)</b>	50W Max
<b>Mountings</b>	Ceiling recessed
<b>Environment</b>	Indoor dry location

### Optical

<b>Lighting type</b>	Direct
<b>Lamp type</b>	QR-CBC 51
<b>Light distribution</b>	Symmetric

### Electrical

<b>Frequency (Hz)</b>	50/60	<b>Driver type</b>	Electronic 12V
<b>Voltage (V)</b>	12.00	<b>Emergency</b>	Without
<b>Lamp holder</b>	GX5.3	<b>Insulation class</b>	III
<b>Dimmable</b>	No		
<b>Driver</b>	Remote excluded		

### Physical

<b>Color</b>	White	<b>Tilt (°)</b>	20
<b>Orientation</b>	Adjustable	<b>Rotation (°)</b>	360
<b>Trim</b>	yes		
<b>Recessed depth (mm)</b>	130		
<b>Weight (kg)</b>	0.12		

### Note

Not suitable for lens accessories.



## Easy Kap 80 Square Adjustable



---

12V Electronic Transformer 20-70W for  
LED Bulbs and Halogen Lamps  
60.9398

---

12V electronic transformer. 220/240V,  
50/60Hz. Adjustable by means of  
"leading and trailing edge"  
60.9424