


## Easy Kap 80 Square Wall-Washer

■ 03.4198.CU - Copper

Recessed luminaire with LED light source. Power supply not included. Installation frame not necessary.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	656
<b>Lamp category</b>	LED	<b>Mountings</b>	Ceiling recessed
<b>Power (W)</b>	9.2W	<b>Environment</b>	Indoor dry location
<b>CCT (K)</b>	3000K		
<b>CRI</b>	90		

### Optical

<b>Lighting type</b>	Indirect, Direct
<b>LED type</b>	LED array
<b>Light distribution</b>	Asymmetric
<b>Optical type</b>	Wall Washer
	Down
<b>Beam angle (°)</b>	28
<b>Beam angle C90-270 (°)</b>	27
<b>Efficiency (lm/W)</b>	71



Beam Angle: 28°

h(m)	E(lx)	D(m)
1	1231	0.64
2	308	1.29
3	137	1.93
4	77	2.57
5	49	3.21

Luminous flux luminaire  
656 lm (EXTREME CUT OFF)

### Electrical


<b>Voltage (V)</b>	17.80	<b>Emergency</b>	Without
<b>Current (mA)</b>	500	<b>Insulation class</b>	III
<b>Dimmable</b>	Yes		
<b>Driver</b>	Remote excluded		
<b>Driver type</b>	Non Dimmable, Dimmable DALI 2, Dimmable 0-10V, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		

### Physical

<b>Color</b>	Copper
<b>Orientation</b>	Fixed
<b>Trim</b>	yes
<b>Recessed depth (mm)</b>	81
<b>Weight (kg)</b>	0.24

### Note

Elliptical lens included.



## Easy Kap 80 Square Wall-Washer



Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.  
60.8847



Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming  
60.9188



Non dimmable continuous current power supply of 220/240V – 50/60Hz with power current selected through adjustable with switch 200 mA – 8,5W / 300 mA – 13W / 350 mA – 15W / 400 mA – 17,5W / 450 mA – 19,5W / 500 mA – 22W  
60.9160



Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W / 750/800/900/1000/1050mA – 38W  
60.9207



Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2  
60.9222



Continuous current power supply, 1-10V, regulable Mains, leading & trailing edge 220/240V – 50/60Hz, 500mA – 10W  
60.9411