




## Easy Kap Ø 80 Plus Adjustable Optic Flood

Update

05.7405.GL - Gold

Recessed luminaire with LED light source. Power supply not included. Installation frame not necessary. Diffusing lens included.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	1014
<b>Lamp category</b>	LED	<b>Mountings</b>	Ceiling recessed
<b>Power (W)</b>	13.4W	<b>Environment</b>	Indoor dry location
<b>CCT (K)</b>	3000K		
<b>CRI</b>	90		

### Optical

<b>Lighting type</b>	Direct
<b>LED type</b>	LED array
<b>Light distribution</b>	Symmetric
<b>Optical type</b>	Flood
<b>Beam angle (°)</b>	45
<b>Beam angle C90-270 (°)</b>	45
<b>Efficiency (lm/W)</b>	75



<b>Beam Angle:</b>	45°	
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>
1	1834	0.83
2	458	1.67
3	204	2.50
4	115	3.34
5	73	4.17

Luminous flux luminaire  
1014 lm (EXTREME CUT OFF)

### Electrical

<b>Voltage (V)</b>	17,8	<b>Emergency</b>	Without
<b>Current (mA)</b>	700	<b>Insulation class</b>	III
<b>Dimmable</b>	Yes		
<b>Driver</b>	Remote excluded		
<b>Driver type</b>	Non Dimmable, Dimmable DALI 2, Dimmable 0-10V, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		

### Physical

<b>Color</b>	Gold	<b>Tilt (°)</b>	20
<b>Orientation</b>	Adjustable	<b>Rotation (°)</b>	360
<b>Trim</b>	yes	<b>Spot diameter (mm)</b>	80
<b>Recessed depth (mm)</b>	150		
<b>Weight (kg)</b>	0,241		

## Easy Kap Ø 80 Plus Adjustable Optic Flood



Continuous current power supply,  
Mains dimming, leading & trailing edge  
220/240V – 50/60Hz, 300mA-14W /  
350mA-17W / 400mA-19W /  
450/500/600/650/700/750/800/900mA –  
20W  
60.9467



Continuous current power supply of  
12-20W, 110/240V – 50/60Hz with power  
current selected through adjustable  
350mA – 17W / 400mA – 19W / 450 / 550  
/ 600 / 700mA – 20W regulable Dali 1 y  
Dali 2  
60.9222



Non dimmable continuous current  
power supply. 15-30W, 220/240V  
-50/60Hz with power current selected  
through adjustable switch. 350mA –  
15W / 400mA – 17W / 450mA – 19W /  
500mA – 22W / 550mA – 24W / 600mA –  
26W / 650mA – 28W / 700mA – 30W no  
regulable  
60.9592



Continuous current power supply,  
dimmable Casambi, 220/240V –  
50/60Hz, 300mA-16W / 350mA-18,5W /  
400mA-21,5W / 450mA-24W / 500mA-  
27W / 600mA-32W / 650mA-35W /  
700mA-36W / 750/800/900/1000/1050mA  
– 38W  
60.9207



Continuous current power supply of  
10-20W, 110/240V – 50/60Hz with power  
current selected through adjustable  
250 mA – 10W / 350 mA – 15W / 400 mA  
– 17W / 450 mA – 19W / 500/550/600/700  
mA – 20W, Dali 1 switch.  
60.8847



Continuous current power supply of  
13-20W, 110/240V – 50/60Hz with power  
current selected through adjustable  
300 mA – 15W / 350 mA – 18W /  
400/450/500/550/600/  
650/700/750/800/850/900 mA – 15W.  
switch. 0/1-10V or push dimming  
60.9188