


Easy Kap Ø 80 Plus Adjustable Optic Medium

Update

■ 05.7404.BU - Blue

Recessed luminaire with LED light source. Power supply not included. Installation frame not necessary. Diffusing lens included.




Main specifications

Number of heads	1	CRI	90
Lamp category	LED	Net lumen (lm)	723
Power (W)	13W	Mountings	Ceiling recessed
System power (W)	13.4	Environment	Indoor dry location
CCT (K)	3000K		

Optical

Lighting type	Direct
LED type	LED array
Light distribution	Symmetric
Optical type	Medium
Beam angle (°)	26
Beam angle C90-270 (°)	26
UGRL	12
Efficiency (lm/W)	53



Beam Angle: 26°

h(m)	E(lx)	D(m)
1	2147	0.47
2	537	0.94
3	239	1.40
4	134	1.87
5	86	2.34

Luminous flux luminaire
723 lm (EXTREME CUT OFF)

Electrical

Voltage (V)	18	Emergency	Without
Current (mA)	700	Insulation class	III
Dimmable	Yes		
Driver	Remote excluded		

Driver type

Non Dimmable,
Dimmable DALI
2, Dimmable 0-
10V, Dimmable
Casambi,
Dimmable 1-
10V, Dimmable
DALI 1, Mains
Cut Dimming

Physical

Color	Blue	Tilt (°)	20
Orientation	Adjustable	Rotation (°)	360
Trim	yes	Spot diameter (mm)	80
Recessed depth (mm)	150	Lifespan (L70 B10)	L80B50
Weight (kg)	0.24		



Easy Kap Ø 80 Plus Adjustable Optic Medium



Continuous current power supply,
Mains dimming, leading & trailing edge
220/240V – 50/60Hz, 300mA-14W /
350mA-17W / 400mA-19W /
450/500/600/650/700/750/800/900mA –
20W
60.9467



Continuous current power supply of
13-20W, 110/240V – 50/60Hz with power
current selected through adjustable
300 mA – 15W / 350 mA – 18W /
400/450/500/550/600/
650/700/750/800/850/900 mA – 15W.
switch. 0/1-10V or push dimming
60.9188



Continuous current power supply of
10-20W, 110/240V – 50/60Hz with power
current selected through adjustable
250 mA – 10W / 350 mA – 15W / 400 mA
– 17W / 450 mA – 19W / 500/550/600/700
mA – 20W, Dali 1 switch.
60.8847



Non dimmable continuous current
power supply. 15-30W, 220/240V
-50/60Hz with power current selected
through adjustable switch. 350mA –
15W / 400mA – 17W / 450mA – 19W /
500mA – 22W / 550mA – 24W / 600mA –
26W / 650mA – 28W / 700mA – 30W no
regulable
60.9592



Continuous current power supply,
dimmable Casambi 220/240V-50/60Hz,
300mA-16W / 350mA-18,5W / 400mA-
21,5W / 450mA-24W / 500mA-27W /
600mA-32W / 650mA-35W / 700mA-36W
/ 750/800/900/1000/1050mA – 38W
60.9207



Continuous current power supply of
12-20W, 110/240V – 50/60Hz with power
current selected through adjustable
350mA – 17W / 400mA – 19W / 450 / 550
/ 600 / 700mA – 20W regulable Dali 1 y
Dali 2
60.9222