

## Easy Kap Ø 80 Plus Fixed Optic Flood

Update

05.7447.B1 - White

Recessed luminaire with LED light source. Power supply not included. Installation frame not necessary. Diffusing lens included.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	1017
<b>Lamp category</b>	LED	<b>Mountings</b>	Ceiling recessed
<b>Power (W)</b>	13.4W	<b>Environment</b>	Indoor dry location
<b>CCT (K)</b>	2700K		
<b>CRI</b>	90		

### Optical

<b>LED type</b>	LED array
<b>Light distribution</b>	Symmetric
<b>Optical type</b>	Flood
<b>Beam angle (°)</b>	50
<b>Beam angle C90-270 (°)</b>	50
<b>Efficiency (lm/W)</b>	75



<b>Beam Angle:</b>	50°		
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>	
1	1575	0.93	
2	394	1.86	
3	175	2.79	
4	98	3.72	
5	63	4.65	



Luminous flux luminaire  
1017 lm (EXTREME CUT OFF)

### Electrical

<b>Voltage (V)</b>	17,8	<b>Emergency</b>	Without
<b>Current (mA)</b>	700	<b>Insulation class</b>	III
<b>Dimmable</b>	Yes		
<b>Driver</b>	Remote excluded		
<b>Driver type</b>	Non Dimmable, Dimmable DALI 2, Dimmable 0-10V, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		

### Physical

<b>Color</b>	White	<b>Spot diameter (mm)</b>	80
<b>Orientation</b>	Fixed		
<b>Trim</b>	yes		
<b>Recessed depth (mm)</b>	150		
<b>Weight (kg)</b>	0,241		



## Easy Kap Ø 80 Plus Fixed Optic Flood



---

Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.  
60.8847



---

Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W / 750/800/900/950/1000/1050/1200mA – 38W  
60.9207



---

Continuous current power supply, Mains dimming, leading & trailing edge 220/240V – 50/60Hz, 300mA-14W / 350mA-17W / 400mA-19W / 450/500/600/650/700/750/800/900mA – 20W  
60.9467



---

Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming  
60.9188



---

Non dimmable continuous current power supply. 15-30W, 220/240V -50/60Hz with power current selected through adjustable switch. 350mA – 15W / 400mA – 17W / 450mA – 19W / 500mA – 22W / 550mA – 24W / 600mA – 26W / 650mA – 28W / 700mA – 30W no regulable  
60.9592



---

Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2  
60.9222