


## Easy Kap Ø 80 Plus Wall-Washer

Update

### 05.7435.CU - Copper

Recessed luminaire with LED light source. Power supply not included. Installation frame not necessary. Elliptical lens included.




### Main specifications

|                         |       |                       |                     |
|-------------------------|-------|-----------------------|---------------------|
| <b>Number of heads</b>  | 1     | <b>CRI</b>            | 90                  |
| <b>Lamp category</b>    | LED   | <b>Net lumen (lm)</b> | 882                 |
| <b>Power (W)</b>        | 13W   | <b>Mountings</b>      | Ceiling recessed    |
| <b>System power (W)</b> | 13.4  | <b>Environment</b>    | Indoor dry location |
| <b>CCT (K)</b>          | 2700K |                       |                     |

### Optical

|                               |             |
|-------------------------------|-------------|
| <b>LED type</b>               | LED array   |
| <b>Light distribution</b>     | Asymmetric  |
| <b>Optical type</b>           | Wall Washer |
|                               | Down        |
| <b>Beam angle (°)</b>         | 28          |
| <b>Beam angle C90-270 (°)</b> | 43          |
| <b>UGRL</b>                   | 23          |
| <b>Efficiency (lm/W)</b>      | 65          |



|                    |              |             |  |
|--------------------|--------------|-------------|--|
| <b>Beam Angle:</b> | 28°          |             |  |
| <b>h(m)</b>        | <b>E(lx)</b> | <b>D(m)</b> |  |
| 1                  | 1334         | 0.64        |  |
| 2                  | 333          | 1.27        |  |
| 3                  | 148          | 1.91        |  |
| 4                  | 83           | 2.55        |  |
| 5                  | 53           | 3.19        |  |


Luminous flux luminaire  
882 lm (EXTREME CUT OFF)

### Electrical

|                     |   |                         |         |
|---------------------|---|-------------------------|---------|
| <b>Voltage (V)</b>  | 18  | <b>Emergency</b>        | Without |
| <b>Current (mA)</b> | 700   | <b>Insulation class</b> | III     |
| <b>Dimmable</b>     | Yes   |                         |         |
| <b>Driver</b>       | Remote excluded   |                         |         |
| <b>Driver type</b>  | Non Dimmable, Dimmable DALI 2, Dimmable 0-10V, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming |                         |         |

### Physical

|                            |        |                           |        |
|----------------------------|--------|---------------------------|--------|
| <b>Color</b>               | Copper | <b>Spot diameter (mm)</b> | 80     |
| <b>Orientation</b>         | Fixed  | <b>Lifespan (L70 B10)</b> | L80B50 |
| <b>Trim</b>                | yes    |                           |        |
| <b>Recessed depth (mm)</b> | 140    |                           |        |
| <b>Weight (kg)</b>         | 0.24   |                           |        |



## Easy Kap Ø 80 Plus Wall-Washer



Non dimmable continuous current power supply. 15-30W, 220/240V -50/60Hz with power current selected through adjustable switch. 350mA – 15W / 400mA – 17W / 450mA – 19W / 500mA – 22W / 550mA – 24W / 600mA – 26W / 650mA – 28W / 700mA – 30W no regulable  
60.9592



Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2  
60.9222



Continuous current power supply, Mains dimming, leading & trailing edge 220/240V – 50/60Hz, 300mA-14W / 350mA-17W / 400mA-19W / 450/500/600/650/700/750/800/900mA – 20W  
60.9467



Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/ 650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming  
60.9188



Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.  
60.8847



Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA- 21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W / 750/800/900/1000/1050mA – 38W  
60.9207