

## Find Me 0 Mono Point (Trim/No Trim)

■ 09.3781.06A - Chrome

Recessed adjustable luminaire for indoor application. Remote power supply 250 mA not included.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	170
<b>Lamp category</b>	LED	<b>Mountings</b>	Ceiling recessed
<b>Power (W)</b>	3W	<b>Environment</b>	Indoor
<b>CCT (K)</b>	2700K		
<b>CRI</b>	90		

### Optical

<b>Lighting type</b>	Direct
<b>LED type</b>	Power LED
<b>Light distribution</b>	Symmetric
<b>Optical type</b>	Medium
<b>Beam angle (°)</b>	26
<b>Beam angle C90-270 (°)</b>	26



<b>Beam Angle: 26°</b>		
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>
1	786	0.45
2	197	0.91
3	87	1.36
4	49	1.82
5	31	2.27

Luminous flux luminaire  
170 lm (EXTREME CUT OFF)

### Electrical



<b>Voltage (V)</b>	12	<b>Emergency</b>	Without
<b>Current (mA)</b>	250	<b>Insulation class</b>	III
<b>Dimmable</b>	Yes		
<b>Driver</b>	Remote		
<b>Driver type</b>	Electronic, Electronic dimmable 1- 10V, Electronic dimmable DALI		

### Physical

<b>Color</b>	Chrome	<b>Rotation (°)</b>	360
<b>Orientation</b>	Adjustable	<b>Spot diameter (mm)</b>	24
<b>Recessed depth (mm)</b>	118		
<b>Weight (kg)</b>	0.14		
<b>Tilt (°)</b>	70		


### Note

Accessories included (honeycomb and screening crosspiece). Remote power supply to be installed in an accessible place. It is not recommended to use dimmable drivers of several brands due to the specific dimming curves of each brand.



Register for service operation is required

POWER SUPPLY



## Find Me 0 Mono Point (Trim/No Trim)



---

Constant voltage supply source of 10W, 100-240V – 50/60Hz with non adjustable 250 mA supply voltage  
60.9389



---

Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.  
60.8847



---

Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2  
60.9222



---

Constant voltage supply source of 20W, 100-240V – 50/60Hz with adjustable 250 mA supply voltage. Dimmable 0-10V  
60.9405



---

Non dimmable continuous current power supply of 220/240V – 50/60Hz with power current selected through adjustable with switch 200 mA – 8,5W / 300 mA – 13W / 350 mA – 15W / 400 mA – 17,5W / 450 mA – 19,5W / 500 mA – 22W  
60.9160



---

Continuous current power supply, Mains dimming, leading & trailing edge 220/240V – 50/60Hz, 300mA-14W / 350mA-17W / 400mA-19W / 450/500/600/650/700/750/800/900mA – 20W  
60.9467



---

Casambi Controller 220-240V. Remote  
Installation  
60.9392