

## Find Me 1 Mono Point (Trim/No Trim)

09.3751.06A - Chrome

Recessed adjustable luminaire for indoor application. Remote power supply 500 mA not included.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	344
<b>Lamp category</b>	LED	<b>Mountings</b>	Ceiling recessed
<b>Power (W)</b>	6W	<b>Environment</b>	Indoor dry location
<b>CCT (K)</b>	2700K		
<b>CRI</b>	90		

### Optical

<b>Lighting type</b>	Direct
<b>LED type</b>	Power LED
<b>Light distribution</b>	Symmetric
<b>Optical type</b>	Spot
<b>Beam angle (°)</b>	14
<b>Beam angle C90-270 (°)</b>	14



<b>Beam Angle:</b>	14°		
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>	
1	4642	0.24	
2	1160	0.48	
3	516	0.72	
4	290	0.95	
5	186	1.19	

Luminous flux luminaire  
344 lm (EXTREME CUT OFF)

### Electrical



<b>Voltage (V)</b>	12	<b>Insulation class</b>	III
<b>Dimmable</b>	Yes		
<b>Driver</b>	Remote excluded		
<b>Driver type</b>	Non Dimmable, Dimmable DALI 2, Dimmable 0-10V, Dimmable Casambi, Dimmable Push, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		
<b>Emergency</b>	Without		

### Physical

<b>Color</b>	Chrome	<b>Rotation (°)</b>	360
<b>Orientation</b>	Adjustable	<b>Spot diameter (mm)</b>	35
<b>Recessed depth (mm)</b>	137		
<b>Weight (kg)</b>	0.23		
<b>Tilt (°)</b>	70		

### Note

Accessories included (honeycomb and screening crosspiece). Remote power supply to be installed in an accessible place.



## Find Me 1 Mono Point (Trim/No Trim)



---

Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W / 750/800/900/950/1000/1050/1200mA – 38W  
60.9207

---

Non dimmable continuous current power supply of 220/240V – 50/60Hz with power current selected through adjustable with switch 200 mA – 8,5W / 300 mA – 13W / 350 mA – 15W / 400 mA – 17,5W / 450 mA – 19,5W / 500 mA – 22W  
60.9160

---

Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.  
60.8847



---

Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/ 650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming  
60.9188

---

Continuous current power supply of 6W, 100V / 14W, 240V – 50/60Hz with 500 mA supply voltage  
60.8880

---

Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2  
60.9222



---

Continuous current power supply, 1-  
10V, regulable Mains, leading & trailing  
edge 220/240V – 50/60Hz, 500mA – 10W  
60.9411