

## Find Me 2 Mono Point (Trim/No Trim)

■ 09.3708.14A - Black


Recessed adjustable luminaire for indoor application. Remote power supply not included.

### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	674
<b>Lamp category</b>	LED	<b>Mountings</b>	Ceiling recessed
<b>Power (W)</b>	10W	<b>Environment</b>	Indoor
<b>CCT (K)</b>	3000K		
<b>CRI</b>	90		

### Optical

<b>Lighting type</b>	Direct
<b>LED type</b>	Power LED
<b>Light distribution</b>	Symmetric
<b>Optical type</b>	Medium
<b>Beam angle (°)</b>	25
<b>Beam angle C90-270 (°)</b>	25



<b>Beam Angle: 25°</b>		
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>
1	3150	0.44
2	788	0.88
3	350	1.32
4	197	1.76
5	126	2.20

Luminous flux luminaire  
674 lm (EXTREME CUT OFF)

### Electrical

<b>Voltage (V)</b>	12.00	<b>Insulation class</b>	III
<b>Dimmable</b>	No		
<b>Driver</b>	Remote		
<b>Driver type</b>	Electronic		
<b>Emergency</b>	Without		

### Physical

<b>Color</b>	Black	<b>Rotation (°)</b>	360
<b>Orientation</b>	Adjustable		
<b>Recessed depth (mm)</b>	187		
<b>Weight (kg)</b>	0.54		
<b>Tilt (°)</b>	70		

### Note

Accessories included (honeycomb and screening crosspiece). Remote power supply to be installed in an accessible place.

## Find Me 2 Mono Point (Trim/No Trim)



Non dimmable continuous current power supply of 15-20W, 110/240V – 50/60Hz, with power current selected through adjustable 350 mA-15W /500 mA / 550 / 700 / 850 mA / 900 mA – 20W switch  
60.8911



Continuous current power supply 220/240V – 50/60Hz. Adjustable Current 300mA-13W / 350mA-15W / 400mA-18W / 450mA-20W / 500mA-22W / 550mA-24W / 600mA-27W / 650mA-29W / 700mA-31W / 750mA-32W / 800mA-33W / 850mA-35W / 900mA-38W / 950mA-40W / 1000/1050mA-42W  
60.9162



Continuous current supply source 240V – 50/60Hz with dimmable DALI 2, push dimming. 300mA-16W / 350mA-18W / 400mA-21W / 500mA-27W / 600mA-32W / 650mA-35W  
700/750/800/900/1000/1050mA-36W  
60.9186



Continuous current power supply, Mains dimming, leading & trailing edge 220/240V – 50/60Hz, 300mA-14W / 350mA-17W / 400mA-19W / 450/500/600/650/700/750/800/900mA – 20W  
60.9467



Continuous current power supply of 25-50W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 25W /500mA – 35W/ 700mA – 50W /750mA – 54W /900/ 1050 mA – 60W switch. Dali 2, 0/1-10V or push dimming  
60.8530



Continuous current power supply of 10W, 110V / 12W, 240V – 50/60Hz with 700 mA supply voltage  
60.8529



---

Continuous current power supply,  
dimmable Casambi, 220/240V –  
50/60Hz, 300mA-16W / 350mA-18,5W /  
400mA-21,5W / 450mA-24W / 500mA-  
27W / 600mA-32W / 650mA-35W /  
700mA-36W / 750/800/900/1000/1050mA  
– 38W  
60.9207