


Johnny 120 Light Source

■ 03.0804.14 - Black

Recessed luminaire with LED light source. Power supply not included. One driver is needed per each light source.




Main specifications

Number of heads	1	Net lumen (lm)	1690
Lamp category	LED	Mountings	Ceiling recessed
Power (W)	18W	Environment	Indoor
CCT (K)	3000K		
CRI	90		

Optical

Lighting type	Direct
LED type	LED array
Light distribution	Symmetric
Optical type	Flood
Beam angle (°)	40
Beam angle C90-270 (°)	40




Beam Angle:	40°		
h(m)	E(lx)	D(m)	
1	4280	0.73	
2	1070	1.46	
3	476	2.18	
4	268	2.91	
5	171	3.64	

Luminous flux luminaire
1690 lm (EXTREME CUT OFF)

Electrical

Frequency (Hz)	50/60	Emergency	Without
Voltage (V)	36.00	Insulation class	III
Dimmable	Yes		
Driver	Remote		
Driver type	Electronic, Electronic dimmable, Electronic dimmable 1-10V, Electronic dimmable DALI		

Certification / Marking




Physical

Color	Black
Orientation	Adjustable
Recessed depth (mm)	160
Weight (kg)	0.50
Tilt (°)	40

Note

Unique reference for Trim or No Trim recessed installation. 08.0555.00=includes white frame to complete Trim finishing. 08.0505.00=includes optional white and black frames to complete Trim finishing.

Johnny 120 Light Source



Honeycomb
08.8428.00

Flood lens
08.8432.00

Elliptical lens
08.8431.00



Snoot shielding cone
08.0526.00

Screening crosspiece
08.8429.00

Continuous current power supply of
13-20W, 110*/240V – 50/60Hz with
power current selected through
adjustable switch. Synchronisation
cables not included.
60.9188



Constant Current Power Supply for
LED. Dimmable DALI. 10-20W
60.8847

Continuous current power supply of
12-20W, 110*/240V – 50/60Hz with
power current selected through
adjustable switch. Synchronisation
cables not included.
60.9188

Continuous current power supply,
Mains dimming 220/240V – 50/60Hz, 12-
20W
60.9188



Continuous current power supply,
dimmable Casambi, 220/240V –
50/60Hz, 35W – 650mA / 36W – 700 mA.
60.9207

Non dimmable continuous current
power supply of 220/240V – 50/60Hz
with power current selected through
adjustable with switch 200mA – 8,5W /
250mA – 11W / 300mA – 13W / 350mA –
15W / 400mA – 17,5W / 450mA 19,5W /
500mA – 22W.
60.9160