

Johnny 120 Light Source

■ 03.0805.14 - Black

Recessed luminaire with LED light source. Power supply not included. One driver is needed per each light source.




Main specifications

Number of heads	1	Net lumen (lm)	1607
Lamp category	LED	Mountings	Ceiling recessed
Power (W)	18W	Environment	Indoor dry location
CCT (K)	2700K		
CRI	90		


Optical

Lighting type	Direct
LED type	LED array
Light distribution	Symmetric
Optical type	Flood
Beam angle (°)	40
Beam angle C90-270 (°)	40



Beam Angle: 40°

h(m)	E(lx)	D(m)
1	4070	0.73
2	1017	1.46
3	452	2.18
4	254	2.91
5	163	3.64

Luminous flux luminaire
1607 lm (EXTREME CUT OFF)

Electrical


Frequency (Hz)	50/60	Emergency	Without
Voltage (V)	36.00	Insulation class	III
Dimmable	Yes		
Driver	Remote excluded		
Driver type	Non Dimmable, Dimmable DALI 2, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		

Physical


Color	Black
Orientation	Adjustable
Recessed depth (mm)	160
Weight (kg)	0.50
Tilt (°)	40

Note

Unique reference for Trim or No Trim recessed installation. 08.0555.00=includes white frame to complete Trim finishing. 08.0505.00=includes optional white and black frames to complete Trim finishing.



Johnny 120 Light Source



Continuous current power supply of 18W, 220/240V – 50/60Hz with 450 mA supply voltage Mains dimming, trailing edge
60.9268

Elliptical lens
08.8431.00

Continuous current power supply. 230/240V – 50/60Hz. Adjustable Current 350mA – 17W / 500mA – 24W / 700/ 750 mA – 32W switch by trailing and leading edge dimming, mains dimming or push dimming
60.8534



Snoot shielding cone
08.0526.00

Flood lens
08.8432.00


Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W /400 mA – 17W /450 mA – 19W /500/550/600/700 mA – 20W, Dali 1 switch.
60.8847



Continuous current power supply of
13-20W, 110/240V – 50/60Hz with power
current selected through adjustable
300 mA – 15W / 350 mA – 18W /
400/450/500/550/600/
650/700/750/800/850/900 mA – 15W.
switch. 0/1-10V or push dimming
60.9188

Snoot shielding cone
08.0526.40

Continuous current power supply
220/240V – 50/60Hz. Adjustable Current
300mA-13W / 350mA-15W / 400mA-18W
/ 450mA-20W / 500mA-22W / 550mA-
24W / 600mA-27W / 650mA-29W /
700mA-31W / 750mA-32W / 800mA-33W
/ 850mA-35W / 900mA-38W / 950mA-
40W / 1000/1050mA-42W
60.9162



Honeycomb
08.8428.00

Continuous current power supply of
30-50W, 110/240V – 50/60Hz with power
current selected through adjustable
300mA – 34W / 350 mA -39W / 400 mA –
45W / 450 – mA – 50W / 500 mA – 56W
/ 550/600/650/700mA – 60W switch.Dali1,
Dali 2, 0/1-10V or push dimming
60.8837

Snoot shielding cone
08.0526.BW