



## Johnny 80 No Trim 1L Square

03.0703.40ANT - White

Recessed luminaire with LED light source. Power supply not included.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	385
<b>Lamp category</b>	LED	<b>Mountings</b>	Ceiling recessed
<b>Power (W)</b>	6.2W	<b>Environment</b>	Indoor dry location
<b>CCT (K)</b>	2700K		
<b>CRI</b>	90		

### Optical

<b>Lighting type</b>	Direct
<b>LED type</b>	Power LED
<b>Light distribution</b>	Symmetric
<b>Optical type</b>	Spot
<b>Beam angle (°)</b>	11
<b>Beam angle C90-270 (°)</b>	11



<b>Beam Angle:</b>	11°		
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>	
1	7360	0.19	
2	1840	0.38	
3	818	0.57	
4	460	0.76	
5	294	0.95	

Luminous flux luminaire  
385 lm (EXTREME CUT OFF)

### Electrical

<b>Frequency (Hz)</b>	50/60	<b>Emergency</b>	Without
<b>Voltage (V)</b>	12	<b>Insulation class</b>	III
<b>Dimmable</b>	Yes		
<b>Driver</b>	Remote excluded		
<b>Driver type</b>	Non Dimmable, Dimmable DALI 2, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		

### Physical

<b>Color</b>	White
<b>Orientation</b>	Adjustable
<b>Recessed depth (mm)</b>	102
<b>Weight (kg)</b>	0.24
<b>Tilt (°)</b>	20

### Note

Accessories included (honeycomb and screening crosspiece).

## Johnny 80 No Trim 1L Square



---


Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.  
60.8847

---

Continuous current power supply, dimmable Casambi, 220/240V – 50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W / 750/800/900/1000/1050mA – 38W  
60.9207

---

Continuous current power supply, 1-10V, regulable Mains, leading & trailing edge 220/240V – 50/60Hz, 500mA – 10W  
60.9411



---

Installation frame No Trim  
08.9103.00

---

Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2  
60.9222

---

Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/ 650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming  
60.9188



---

Non dimmable continuous current  
power supply of 220/240V – 50/60Hz  
with power current selected through  
adjustable with switch 200 mA – 8,5W /  
300 mA – 13W / 350 mA – 15W / 400 mA  
– 17,5W / 450 mA – 19,5W / 500 mA –  
22W  
60.9160