# Johnny 80 Semi-Recessed 2L Square

## 03.0730.CEA - Concrete/Black

Semi-recessed luminaire with LED light source. Power supply not included. Requires one power supply for each optic body.




## Main specifications

| | | | |
|---|---|---|---|
| **Number of heads** | 2 | **Net lumen (lm)** | 399 |
| **Lamp category** | LED | **Mountings** | Ceiling recessed |
| **Power (W)** | 6.2W | **Environment** | Indoor dry location |
| **CCT (K)** | 3000K | | |
| **CRI** | 90 | | |

## Optical

| | |
|---|---|
| **Lighting type** | Direct |
| **LED type** | Power LED |
| **Light distribution** | Symmetric |
| **Optical type** | Spot |
| **Beam angle (°)** | 11 |
| **Beam angle C90-270 (°)** | 11 |




Luminous flux luminaire
399 lm (EXTREME CUT OFF)

Beam Angle: 11°

| h(m) | E(lx) | D(m) |
|---|---|---|
| 1 | 7629 | 0.19 |
| 2 | 1907 | 0.38 |
| 3 | 848 | 0.57 |
| 4 | 477 | 0.76 |
| 5 | 305 | 0.95 |

## Electrical

| | | | |
|---|---|---|---|
| **Frequency (Hz)** | 50/60 | **Emergency** | Without |
| **Voltage (V)** | 12 | **Insulation class** | III |
| **Dimmable** | Yes | | |
| **Driver** | Remote excluded | | |
| **Driver type** | Non Dimmable, Dimmable DALI 2, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming | | |

## Physical

| | |
|---|---|
| **Color** | Concrete/Black |
| **Orientation** | Adjustable |
| **Recessed depth (mm)** | 152 |
| **Weight (kg)** | 0.65 |
| **Tilt (°)** | 20 |

## Note

Accessories included (honeycomb and screening crosspiece).

# Johnny 80 Semi-Recessed 2L Square

Non dimmable continuous current power supply of 220/240V – 50/60Hz with power current selected through adjustable with switch 200 mA – 8,5W / 300 mA – 13W / 350 mA – 15W / 400 mA – 17,5W / 450 mA – 19,5W / 500 mA – 22W
60.9160

Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/ 650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming
60.9188

Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W /400 mA – 17W /450 mA – 19W /500/550/600/700 mA – 20W, Dali 1 switch.
60.8847

Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2
60.9222

Continuous current power supply, 1-10V, regulable Mains, leading & trailing edge 220/240V – 50/60Hz, 500mA – 10W
60.9411

Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W /750/800/900/1000/1050mA – 38W
60.9207