



Kap 80 Square Adjustable Optic Spot

■ 03.4543.BU - Blue

Recessed luminaire with LED light source. Power supply not included.




Main specifications

Number of heads	1	CRI	90
Lamp category	LED	Net lumen (lm)	674
Power (W)	9.2W	Mountings	Ceiling recessed
System power (W)	9.2	Environment	Indoor dry location
CCT (K)	2700K		

Optical

Lighting type	Direct
LED type	LED array
Light distribution	Symmetric
Optical type	Spot
Beam angle (°)	18
Beam angle C90-270 (°)	18
UGRL	15
Efficiency (lm/W)	73



Beam Angle: 18°

h(m)	E(lx)	D(m)
1	2650	0.31
2	662	0.62
3	294	0.93
4	166	1.24
5	106	1.55

Luminous flux luminaire
674 lm (EXTREME CUT OFF)

Electrical

Voltage (V)	18	Emergency	Without
Current (mA)	500	Insulation class	III
Dimmable	Yes		
Driver	Remote excluded		
Driver type	Non Dimmable, Dimmable DALI 2, Dimmable 0-10V, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		


Physical

Color	Blue	Rotation (°)	360
Orientation	Adjustable	Lifespan (L70 B10)	L80B50
Recessed depth (mm)	91		
Weight (kg)	0.24		
Tilt (°)	20		

Note

Diffusing lens included.

Kap 80 Square Adjustable Optic Spot



Continuous current power supply,
dimmable Casambi 220/240V-50/60Hz,
300mA-16W / 350mA-18,5W / 400mA-
21,5W / 450mA-24W / 500mA-27W /
600mA-32W / 650mA-35W / 700mA-36W
/750/800/900/1000/1050mA – 38W
60.9207

Installation frame No Trim
08.9103.00

Continuous current power supply of
10-20W, 110/240V – 50/60Hz with power
current selected through adjustable
250 mA – 10W / 350 mA – 15W /400 mA
– 17W /450 mA – 19W /500/550/600/700
mA – 20W, Dali 1 switch.
60.8847



Continuous current power supply of
12-20W, 110/240V – 50/60Hz with power
current selected through adjustable
350mA – 17W / 400mA – 19W / 450 / 550
/ 600 / 700mA – 20W regulable Dali 1 y
Dali 2
60.9222

Non dimmable continuous current
power supply of 220/240V – 50/60Hz
with power current selected through
adjustable with switch 200 mA – 8,5W /
300 mA – 13W / 350 mA – 15W / 400 mA
– 17,5W / 450 mA – 19,5W / 500 mA –
22W
60.9160

Continuous current power supply of
13-20W, 110/240V – 50/60Hz with power
current selected through adjustable
300 mA – 15W / 350 mA – 18W /
400/450/500/550/600/
650/700/750/800/850/900 mA – 15W.
switch. 0/1-10V or push dimming
60.9188



Continuous current power supply, 1-
10V, regulable Mains, leading & trailing
edge 220/240V – 50/60Hz, 500mA – 10W
60.9411