


## Kap 80 Square Wall-Washer

■ 03.4190.BU - Blue

Recessed luminaire with LED light source. Power supply not included.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	636
<b>Lamp category</b>	LED	<b>Mountings</b>	Ceiling recessed
<b>Power (W)</b>	8.7W	<b>Environment</b>	Indoor dry location
<b>CCT (K)</b>	3000K		
<b>CRI</b>	90		

### Optical

<b>Lighting type</b>	Indirect, Direct
<b>LED type</b>	LED array
<b>Light distribution</b>	Asymmetric
<b>Optical type</b>	Wall Washer
	Down
<b>Beam angle (°)</b>	26
<b>Beam angle C90-270 (°)</b>	27
<b>Efficiency (lm/W)</b>	73



<b>Beam Angle: 26°</b>		
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>
1	1211	0.63
2	303	1.25
3	135	1.88
4	76	2.51
5	48	3.14

Luminous flux luminaire  
636 lm (EXTREME CUT OFF)

### Electrical


<b>Voltage (V)</b>	17.80	<b>Emergency</b>	Without
<b>Current (mA)</b>	500	<b>Insulation class</b>	III
<b>Dimmable</b>	Yes		
<b>Driver</b>	Remote excluded		
<b>Driver type</b>	Non Dimmable, Dimmable DALI 2, Dimmable 0-10V, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		

### Physical

<b>Color</b>	Blue
<b>Orientation</b>	Fixed
<b>Recessed depth (mm)</b>	81
<b>Weight (kg)</b>	0.24

### Note

Diffusing lens included.



## Kap 80 Square Wall-Washer



---

Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.  
60.8847



---

Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/ 650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming  
60.9188




---

Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W / 750/800/900/1000/1050mA – 38W  
60.9207



---

Non dimmable continuous current power supply of 220/240V – 50/60Hz with power current selected through adjustable with switch 200 mA – 8,5W / 300 mA – 13W / 350 mA – 15W / 400 mA – 17,5W / 450 mA – 19,5W / 500 mA – 22W  
60.9160



---

Installation frame No Trim  
08.9103.00



---

Continuous current power supply, 1-10V, regulable Mains, leading & trailing edge 220/240V – 50/60Hz, 500mA – 10W  
60.9411



---

Continuous current power supply of  
12-20W, 110/240V – 50/60Hz with power  
current selected through adjustable  
350mA – 17W / 400mA – 19W / 450 / 550  
/ 600 / 700mA – 20W regulable Dali 1 y  
Dali 2  
60.9222