


Update

Recessed luminaire with LED light source. Power supply not included. Diffusing lens included.



CRI	90
Net lumen (lm)	906
Mountings	Ceiling recessed
Environment	Indoor dry location

F F7 F 07

Luminous flux lumineuse
906 lm (EXTREME CUT OFF)

Emergency Insulation class	Without III
-------------------------------	----------------

Rotation (°)	360
Spot diameter (mm)	74
Lifespan (L70 B10)	L80B50

Kap Ø 80 Plus Adjustable Optic Flood



Continuous current power supply,
Mains dimming, leading & trailing edge
220/240V – 50/60Hz, 300mA-14W /
350mA-17W / 400mA-19W /
450/500/600/650/700/750/800/900mA –
20W
60.9467



Continuous current power supply,
dimmable Casambi 220/240V-50/60Hz,
300mA-16W / 350mA-18,5W / 400mA-
21,5W / 450mA-24W / 500mA-27W /
600mA-32W / 650mA-35W / 700mA-36W
/750/800/900/1000/1050mA – 38W
60.9207



Installation frame No Trim
08.9102.00



Continuous current power supply of
10-20W, 110/240V – 50/60Hz with power
current selected through adjustable
250 mA – 10W / 350 mA – 15W / 400 mA
– 17W / 450 mA – 19W / 500/550/600/700
mA – 20W, Dali 1 switch.
60.8847



Continuous current power supply of
12-20W, 110/240V – 50/60Hz with power
current selected through adjustable
350mA – 17W / 400mA – 19W / 450 / 550
/ 600 / 700mA – 20W regulable Dali 1 y
Dali 2
60.9222



Non dimmable continuous current
power supply. 15-30W, 220/240V
-50/60Hz with power current selected
through adjustable switch. 350mA –
15W / 400mA – 17W / 450mA – 19W /
500mA – 22W / 550mA – 24W / 600mA –
26W / 650mA – 28W / 700mA – 30W no
regulable
60.9592



Continuous current power supply of
13-20W, 110/240V – 50/60Hz with power
current selected through adjustable
300 mA – 15W / 350 mA – 18W /
400/450/500/550/600/
650/700/750/800/850/900 mA – 15W.
switch. 0/1-10V or push dimming
60.9188