

## Light Shadow Optic Wide Flood On Board Dimmer

■ ■ 03.9661.14A - Black/Black

LED lighting module, with 4 spotlights and low glare, to be installed in the The Running Magnet system. DC/DC, built-in electronic current converter.




### Main specifications

|                  |       |                |                     |
|------------------|-------|----------------|---------------------|
| Lamp category    | LED   | Net lumen (lm) | 731                 |
| Power (W)        | 10.8W | Mountings      | Track               |
| System power (W) | 13.4  | Environment    | Indoor dry location |
| CCT (K)          | 2700K |                |                     |
| CRI              | 90    |                |                     |

### Optical

|                        |            |
|------------------------|------------|
| Lighting type          | Direct     |
| LED type               | Power LED  |
| Light distribution     | Symmetric  |
| Optical type           | Wide flood |
| Beam angle (°)         | 47         |
| Beam angle C90-270 (°) | 47         |
| UGRL                   | 11         |
| Efficiency (lm/W)      | 54.55      |



Beam Angle: 45°

h(m) E(lx) D(m)

1 1363 0.83

2 341 1.67

3 151 2.50

4 85 3.34

5 55 4.17

Luminous flux luminaire  
731 lm (EXTREME CUT OFF)

### Electrical

|             |                 |                  |     |
|-------------|-----------------|------------------|-----|
| Voltage (V) | 24.00           | Insulation class | III |
| Dimmable    | Yes             |                  |     |
| Driver      | Remote excluded |                  |     |
| Driver type | Dimmer on board |                  |     |
| Emergency   | Without         |                  |     |

### Physical

|                    |             |
|--------------------|-------------|
| Color              | Black/Black |
| Orientation        | Fixed       |
| Weight (kg)        | 0.34        |
| Length (mm)        | 140         |
| Lifespan (L70 B10) | L80B50      |

### Note

For wireless lighting control, choose integrated Casambi versions.

