



## Light Shadow Pro Ø 90 Fixed Optic Wide Flood

New

03.9967.GL - Gold

LED lighting module, with low glare, to be inserted in the recessed frames (not included), installation through a bayonet system with interchangeable spots. Remote driver not included.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	1994
<b>Lamp category</b>	LED	<b>Mountings</b>	Recessed
<b>Power (W)</b>	22W	<b>Environment</b>	Indoor dry location
<b>CCT (K)</b>	3000K		
<b>CRI</b>	90		

### Optical

<b>Lighting type</b>	Direct
<b>LED type</b>	LED array
<b>Light distribution</b>	Symmetric
<b>Optical type</b>	Wide flood
<b>Beam angle (°)</b>	49
<b>Beam angle C90-270 (°)</b>	49



<b>Beam Angle:</b>	49°		
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>	
1	3262	0.91	
2	815	1.82	
3	362	2.74	
4	204	3.65	
5	130	4.56	

Luminous flux luminaire  
1994 lm

### Electrical

<b>Current (mA)</b>	600	<b>Insulation class</b>	III
<b>Dimmable</b>	Yes		
<b>Driver</b>	Remote excluded		
<b>Driver type</b>	Non Dimmable, Dimmable DALI 2, Dimmable, Dimmable Casambi, Dimmable 1-10V, Dimmable DALI 1, Mains Cut Dimming		
<b>Emergency</b>	Without		

### Physical

<b>Color</b>	Gold
<b>Orientation</b>	Fixed
<b>Recessed depth (mm)</b>	129
<b>Weight (kg)</b>	0.54
<b>Spot diameter (mm)</b>	90

### Note

Please select 500 mA setting in the remote driver to match the power of the Adjustable version.

# Light Shadow Pro Ø 90 Fixed Optic Wide Flood



---

Continuous current power supply, 0/1-10V dimmable, 220/240V – 50/60Hz, 300mA-16W / 350mA-18W / 400mA-21W / 500mA-27W / 600mA-32W / 650mA-35W / 700/750/800/900/950/1000/1050mA-36W  
60.9439

---

Installation Frame Trim  
08.0161.40

---

Installation Frame No Trim  
08.0193.00



---

Continuous current supply source 240V – 50/60Hz with dimmable DALI 2, push dimming. 300mA-16W / 350mA-18W / 400mA-21W / 500mA-27W / 600mA-32W / 650mA-35W / 700/750/800/900/950/1000/1050mA-38W  
60.9186

---

Non dimmable continuous current power supply of 24W, 110/277V – 50/60Hz, with power current selected through adjustable 500 mA/600 mA switch  
60.9523

---

Installation Frame Trim  
08.0161.14



---

Continuous current power supply  
220/240V – 50/60Hz. Adjustable Current  
300mA-13W / 350mA-15W / 400mA-18W  
/ 450mA-20W / 500mA-22W / 550mA-  
24W / 600mA-27W / 650mA-29W /  
700mA-31W / 750mA-32W / 800mA-33W  
/ 850mA-35W / 900mA-38W / 950mA-  
40W / 1000/1050mA-42W  
60.9162

---

Continuous current power supply of  
13-20W, 110/240V – 50/60Hz with power  
current selected through adjustable  
300 mA – 15W / 350 mA – 18W /  
400/450/500/550/600/  
650/700/750/800/850/900 mA – 15W.  
switch. 0/1-10V or push dimming  
60.9188

---

Continuous current power supply of  
12-20W, 110/240V – 50/60Hz with power  
current selected through adjustable  
350mA – 17W / 400mA – 19W / 450 / 550  
/ 600 / 700mA – 20W regulable Dali 1 y  
Dali 2  
60.9222



---

Continuous current power supply,  
Mains dimming, leading & trailing edge  
220/240V – 50/60Hz, 300mA-14W /  
350mA-17W / 400mA-19W /  
450/500/600/650/700/750/800/900mA –  
20W  
60.9467