









Decofix Square 2L

09.3105.14A - Black

Recessed luminaire with 2 lights for LED light source. Power supply not included. Requires one power supply for each optic body included.

Main specifications Number of heads Lamp category Power (W) CCT (K) CRI	2 LED 9.2W 3000K 80	Net lumen (lm) Mountings Environment	438 Ceiling rece Indoor dry l			
Optical Lighting type LED type Light distribution Beam angle (°) Beam angle C90-270 (°)	Direct LED array Symmetric 39 36	90° 60° 30° 866 cd Luminous flux lu 438 lm (EXTREME		Beam <u>h(m)</u> <u>1</u> <u>2</u> <u>3</u> <u>4</u> 5	Angle: E(lx) 866 216 96 54 35	39° D(m) 0.64 1.28 1.92 2.55 3.19
Electrical Frequency (Hz) Dimmable Driver Driver type Emergency	50/60 Yes Remote excluded Non Dimmable, Dimmable DALI 2, Dimmable Casambi, Dimmable 1- 10V, Dimmable DALI 1, Mains Cut Dimming Without	Insulation class	III			
Physical Color Orientation Recessed depth (mm) Weight (kg)	Black Fixed 126 0.80					

Note

All versions have interchangeable screening cylinders in 3 colours: black, gold or silver, incorporated into the light fixture.

Decofix Square 2L







Non dimmable continuous current power supply of 220/240V – 50/60Hz with power current selected through adjustable with switch 200 mA – 8,5W / 300 mA – 13W / 350 mA – 15W / 400 mA – 17,5W / 450 mA – 19,5W / 500 mA – 22W 60.9160

Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W /400 mA – 17W /450 mA – 19W /500/550/600/700 mA – 20W, Dali 1 switch. 60.8847 Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W /750/800/900/1000/1050mA – 38W 60.9207







Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/ 650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming 60.9188

Continuous current power supply, 1-10V, regulable Mains, leading & trailing edge 220/240V – 50/60Hz, 500mA – 10W 60.9411 Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2 60.9222