




## Easy Kap Ø 80 Plus Fixed Optic Medium

Update

■ 05.7430.74 - Black

Recessed luminaire with LED light source. Power supply not included. Installation frame not necessary. Diffusing lens included.




### Main specifications

Number of heads	1	Net lumen (lm)	822
Lamp category	LED	Mountings	Ceiling recessed
Power (W)	13.4W	Environment	Indoor
CCT (K)	3000K		
CRI	90		

### Optical

Lighting type	Direct
LED type	LED array
Light distribution	Symmetric
Optical type	Medium
Beam angle (°)	25
Beam angle C90-270 (°)	25
Efficiency (lm/W)	61



Beam Angle:	25°
h(m)	E(lx) D(m)
1	2715 0.45
2	679 0.89
3	302 1.34
4	170 1.79
5	109 2.23

Luminous flux luminaire  
822 lm (EXTREME CUT OFF)

### Electrical

Voltage (V)	17,8	Emergency	Without
Current (mA)	700	Insulation class	III
Dimmable	Yes		
Driver	Remote		
Driver type	Electronic, Electronic dimmable, Electronic dimmable 1-10V, Electronic dimmable DALI		

### Physical

Color	Black	Spot diameter (mm)	80
Orientation	Fixed		
Trim	yes		
Recessed depth (mm)	150		
Weight (kg)	0,241		

## Easy Kap Ø 80 Plus Fixed Optic Medium



Continuous current power supply,  
Mains dimming, leading & trailing edge  
220/240V – 50/60Hz, 300mA-14W /  
350mA-17W / 400mA-19W /  
450/500/600/650/700/750/800/900mA –  
20W  
60.9467



Continuous current power supply,  
dimmable Casambi, 220/240V –  
50/60Hz, 300mA-16W / 350mA-18,5W /  
400mA-21,5W / 450mA-24W / 500mA-  
27W / 600mA-32W / 650mA-35W /  
700mA-36W /750/800/900/1000/1050mA  
– 38W  
60.9207



Continuous current power supply of  
10-20W, 110/240V – 50/60Hz with power  
current selected through adjustable  
250 mA – 10W / 350 mA – 15W /400 mA  
– 17W /450 mA – 19W /500/550/600/700  
mA – 20W, Dali 1 switch.  
60.8847



Continuous current power supply of  
13-20W, 110/240V – 50/60Hz with power  
current selected through adjustable  
300 mA – 15W / 350 mA – 18W /  
400/450/500/550/600/  
650/700/750/800/850/900 mA – 15W.  
switch. 0/1-10V or push dimming  
60.9188



Continuous current power supply of  
12-20W, 110/240V – 50/60Hz with power  
current selected through adjustable  
350mA – 17W / 400mA – 19W / 450 / 550  
/ 600 / 700mA – 20W regulable Dali 1 y  
Dali 2  
60.9222



Non dimmable continuous current  
power supply. 15-30W, 220/240V  
-50/60Hz with power currentselected  
through adjustable switch. 350mA –  
15W / 400mA – 17W / 450mA – 19W /  
500mA – 22W / 550mA – 24W / 600mA –  
26W / 650mA – 28W / 700mA – 30W no  
regulable  
60.9592