


Update


Recessed luminaire with LED light source. Power supply not included. Diffusing lens included.



Number of heads	1
Lamp category	LED
Power (W)	13W
System power (W)	13.4
CCT (K)	2700K

CRI	90
Net lumen (lm)	987
Mountings	Ceiling recessed
Environment	Indoor dry location

LED type	LED array
Light distribution	Symmetric
Optical type	Flood
Beam angle (°)	45
Beam angle C90-270 (°)	45
UGRL	15
Efficiency (lm/W)	73



Beam Angle: 45°

h(m)	E(lx)	D(m)
1	1785	0.83
2	446	1.67
3	198	2.50
4	112	3.34
5	71	4.17

Luminous flux lumineire
987 lm (EXTREME CUT OFF)

Voltage (V)	18
Current (mA)	700
Dimmable	Yes
Driver	Remote excluded
Driver type	Non Dimmable, Dimmable DALI 2, Dimmable 0- 10V, Dimmable Casambi, Dimmable 1- 10V, Dimmable DALI 1, Mains Cut Dimming

Emergency	Without
Insulation class	III

Color	Gold
Orientation	Adjustable
Recessed depth (mm)	150
Weight (kg)	0.24
Tilt (°)	20

Rotation (°)	360
Spot diameter (mm)	74
Lifespan (L70 B10)	L80B50

Kap Ø 80 Plus Adjustable Optic Flood



Non dimmable continuous current power supply. 15-30W, 220/240V -50/60Hz with power current selected through adjustable switch. 350mA – 15W / 400mA – 17W / 450mA – 19W / 500mA – 22W / 550mA – 24W / 600mA – 26W / 650mA – 28W / 700mA – 30W no regulable
60.9592



Installation frame No Trim
08.9102.00



Continuous current power supply, Mains dimming, leading & trailing edge 220/240V – 50/60Hz, 300mA-14W / 350mA-17W / 400mA-19W / 450/500/600/650/700/750/800/900mA – 20W
60.9467



Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/ 650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming
60.9188



Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.
60.8847



Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA- 21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W / 750/800/900/1000/1050mA – 38W
60.9207



Continuous current power supply of
12-20W, 110/240V – 50/60Hz with power
current selected through adjustable
350mA – 17W / 400mA – 19W / 450 / 550
/ 600 / 700mA – 20W regulable Dali 1 y
Dali 2
60.9222