



03.6154.30A - White

Recessed luminaire with LED light source. Power supply not included.



| | | | |
|-----------------|-------|----------------|---------------------|
| Number of heads | 1 | Net lumen (lm) | 436 |
| Lamp category | LED | Mountings | Ceiling recessed |
| Power (W) | 9.2W | Environment | Indoor dry location |
| CCT (K) | 3000K | | |
| CRI | 80 | | |

| | |
|------------------------|------------|
| Lighting type | Direct |
| LED type | LED array |
| Light distribution | Symmetric |
| Optical type | Wide flood |
| Beam angle (°) | 83 |
| Beam angle C90-270 (°) | 83 |



Luminous flux lumineuse
436 lm

Beam Angle: 83°

| h(m) | E(lx) | D(m) |
|------|-------|------|
| 1 | 309 | 1.77 |
| 2 | 77 | 3.55 |
| 3 | 34 | 5.32 |
| 4 | 19 | 7.09 |
| 5 | 12 | 8.87 |

| | | | |
|-----------------------|---|-------------------------|-----|
| Frequency (Hz) | 50/60 | Insulation class | III |
| Dimmable | Yes | | |
| Driver | Remote excluded | | |
| Driver type | Non Dimmable, Dimmable Push, Dimmable 1- 10V, Dimmable DALI 1, Mains Cut Dimming | | |
| Emergency | Without | | |

Emergency

| | |
|---------------------|-------|
| Color | White |
| Orientation | Fixed |
| Recessed depth (mm) | 98 |
| Weight (kg) | 0.35 |

Wan Downlight



Continuous current power supply of 13-20W, 110/240V – 50/60Hz with power current selected through adjustable 300 mA – 15W / 350 mA – 18W / 400/450/500/550/600/ 650/700/750/800/850/900 mA – 15W. switch. 0/1-10V or push dimming
60.9188

Continuous current power supply of 12-20W, 110/240V – 50/60Hz with power current selected through adjustable 350mA – 17W / 400mA – 19W / 450 / 550 / 600 / 700mA – 20W regulable Dali 1 y Dali 2
60.9222

Non dimmable continuous current power supply of 220/240V – 50/60Hz with power current selected through adjustable with switch 200 mA – 8,5W / 300 mA – 13W / 350 mA – 15W / 400 mA – 17,5W / 450 mA – 19,5W / 500 mA – 22W
60.9160



Continuous current power supply, dimmable Casambi 220/240V-50/60Hz, 300mA-16W / 350mA-18,5W / 400mA-21,5W / 450mA-24W / 500mA-27W / 600mA-32W / 650mA-35W / 700mA-36W / 750/800/900/1000/1050mA – 38W
60.9207

Continuous current power supply of 10-20W, 110/240V – 50/60Hz with power current selected through adjustable 250 mA – 10W / 350 mA – 15W / 400 mA – 17W / 450 mA – 19W / 500/550/600/700 mA – 20W, Dali 1 switch.
60.8847

Continuous current power supply, 1-10V, regulable Mains, leading & trailing edge 220/240V – 50/60Hz, 500mA – 10W
60.9411