

Easy Kap Ø 105 Adjustable

■ 05.7035.BU - Blue

Recessed 12V lamp luminaire. Remote transformer not included. Installation frame not necessary.



Main specifications

| | |
|---------------|---------------------|
| Lamp category | LED |
| Mountings | Ceiling recessed |
| Environment | Indoor dry location |

Optical

| | |
|--------------------|-----------|
| Lighting type | Direct |
| Lamp type | QR-CBC 51 |
| Light distribution | Symmetric |

Electrical


| | | | |
|----------------|-----------------|------------------|---------|
| Frequency (Hz) | 50/60 | Emergency | Without |
| Voltage (V) | 12 | Insulation class | II |
| Lamp holder | GX5.3 | | |
| Driver | Remote excluded | | |
| Driver type | Electronic 12V | | |

Physical

| | | | |
|---------------------|------------|--------------------|-----|
| Color | Blue | Tilt (°) | 20 |
| Orientation | Adjustable | Rotation (°) | 360 |
| Trim | yes | Spot diameter (mm) | 111 |
| Recessed depth (mm) | 125 | | |
| Weight (kg) | 0,45 | | |

Note

Not suitable for lens accessories.



Easy Kap Ø 105 Adjustable



12V Electronic Transformer 20-70W for
LED Bulbs and Halogen Lamps
60.9398

12V electronic transformer. 220/240V,
50/60Hz. Adjustable by means of
"leading and trailing edge"
60.9424