

## Easy Kap Ø 105 Adjustable

■ 05.7035.CU - Copper

Recessed 12V lamp luminaire. Remote transformer not included. Installation frame not necessary.



### Main specifications

|               |                     |
|---------------|---------------------|
| Lamp category | LED                 |
| Mountings     | Ceiling recessed    |
| Environment   | Indoor dry location |

### Optical

|                    |           |
|--------------------|-----------|
| Lighting type      | Direct    |
| Lamp type          | QR-CBC 51 |
| Light distribution | Symmetric |

### Electrical


|                |                 |                  |         |
|----------------|-----------------|------------------|---------|
| Frequency (Hz) | 50/60           | Emergency        | Without |
| Voltage (V)    | 12              | Insulation class | II      |
| Lamp holder    | GX5.3           |                  |         |
| Driver         | Remote excluded |                  |         |
| Driver type    | Electronic 12V  |                  |         |

### Physical

|                     |            |                    |     |
|---------------------|------------|--------------------|-----|
| Color               | Copper     | Tilt (°)           | 20  |
| Orientation         | Adjustable | Rotation (°)       | 360 |
| Trim                | yes        | Spot diameter (mm) | 111 |
| Recessed depth (mm) | 125        |                    |     |
| Weight (kg)         | 0,45       |                    |     |

### Note

Not suitable for lens accessories.



## Easy Kap Ø 105 Adjustable



---

12V electronic transformer. 220/240V,  
50/60Hz. Adjustable by means of  
"leading and trailing edge"  
60.9424

---

12V Electronic Transformer 20-70W for  
LED Bulbs and Halogen Lamps  
60.9398