


Easy Kap Ø 80 Fixed

■ 03.4210.CU - Copper

Recessed 12V lamp luminaire. Remote transformer not included. Installation frame not necessary.

Recessed 12V lamp luminaire. Remote transformer not included. Installation frame not necessary.




Main specifications

Number of heads	1	Environment	Indoor
Lamp category	Halogen, LED retrofit		
Power (W)	50W Max		
Net lumen (lm)	668		
Mountings	Ceiling recessed		

Optical

Lighting type	Direct
Lamp type	QR-CBC 51
Light distribution	Symmetric
Beam angle (°)	17
Beam angle C90-270 (°)	17



Beam Angle: 17°

h(m)	E(lx)	D(m)
1	5161	0.30
2	1290	0.61
3	573	0.91
4	323	1.22
5	206	1.52

Luminous flux luminaire
848 lm (EXTREME CUT OFF)

Electrical

Frequency (Hz)	50/60	Driver type	Electronic
Voltage (V)	12.00	Emergency	Without
Lamp holder	GX5.3	Insulation class	III
Dimmable	No		
Driver	Remote		

Physical

Color	Copper	Spot diameter (mm)	80
Orientation	Fixed		
Trim	yes		
Recessed depth (mm)	130		
Weight (kg)	0.12		

Note

Not suitable for lens accessories.



Easy Kap Ø 80 Fixed



12V Electronic Transformer 20-70W for
LED Bulbs and Halogen Lamps
60.9398

12V electronic transformer. 220/240V,
50/60Hz. Adjustable by means of
"leading and trailing edge"
60.9424