

## Find Me 0

### 09.3803.CZA - Bronze

LED accent lighting module to be installed in the Zero Track system. Incorporated DC/DC electronic converter. Module regulated via Casambi driver, 1-10-V or DALI in broadcast mode. To individually control the lights, select integrated Casambi versions.




### Main specifications

<b>Number of heads</b>	1	<b>Net lumen (lm)</b>	179
<b>Lamp category</b>	LED	<b>Mountings</b>	Track
<b>Power (W)</b>	3.5W	<b>Environment</b>	Indoor dry location
<b>CCT (K)</b>	2700K		
<b>CRI</b>	90		


### Optical

<b>Lighting type</b>	Direct
<b>LED type</b>	Power LED
<b>Light distribution</b>	Symmetric
<b>Optical type</b>	Medium
<b>Beam angle (°)</b>	25
<b>Beam angle C90-270 (°)</b>	25



<b>Beam Angle:</b>	25°		
<b>h(m)</b>	<b>E(lx)</b>	<b>D(m)</b>	
1	929	0.45	
2	232	0.89	
3	103	1.34	
4	58	1.79	
5	37	2.23	

Luminous flux luminaire  
179 lm



### Electrical

<b>Voltage (V)</b>	24	<b>Insulation class</b>	III
<b>Dimmable</b>	Yes		
<b>Driver</b>	Remote excluded		
<b>Driver type</b>	Non Dimmable, Dimmable, Casambi, Dimmable 1-10V, Dimmable DALI 1		
<b>Emergency</b>	Without		

### Physical

<b>Color</b>	Bronze	<b>Spot diameter (mm)</b>	24
<b>Orientation</b>	Adjustable	<b>Length (mm)</b>	24
<b>Weight (kg)</b>	0.06		
<b>Tilt (°)</b>	90		
<b>Rotation (°)</b>	360		

### Note

Accessories included (honeycomb and screening crosspiece).

